

LA GARD

700 SERIES comparison:



700 BASIC



702 COMBOPLUS



702 AUDIT



703 2FA



704 MASTER

Replaces	LG BASIC	39E	66E AND 66E SUPRA	66E WITH DALLAS	LG MASTER
Electronic Manipulation Defence (EMD)	YES	YES	YES	YES	YES
Digital pad to lock communication	YES	YES	YES	YES	YES
Pad to Lock encryption	YES	YES	YES	YES	YES
Updateable firmware	YES	YES	YES	YES	YES
Combination Length	6 no user ID	11 (2id + 6-9)	11 (2id + 6-9)	11 (2id + 6-9)	11 (2id + 6-9)
Number of Users	1M/1m/1u	1M/1m/30u	1M/1m/30u	1M/1m/30u	1M/2m/50u
Legacy LG Basic Mode	YES	NO	NO	NO	NO
Display Keypad OLED Screen	NO	YES	YES	YES	YES
Back Lit Keypad	YES	YES	YES	YES	YES
Low profile Key Pad option	NO	YES	YES	YES	YES
High profile Pad	YES	YES	YES	YES	YES
Simple Battery Draw in High Profile Pad	YES	YES	YES	YES	YES
Bolt Options	Swing and Deadbolt	Swing, Spring and Deadbolt	Swing, Spring and Deadbolt	Swing, Spring and Deadbolt	Swing, Spring and Deadbolt
Redundant Lock	NO	NO	YES	YES	YES
Time Delay	NO	0-99min	0-99 min	0-99min	0-99min
Time Delay Override	NO	YES	YES	YES	YES
Time Lock Schedule	NO	NO	NO	NO	YES
Time Window	NO	1-60min	1-60 min	1-60min	1-60min
Time Dependent Functions	NO	NO	NO	NO	YES
Audit	NO	500 (EVENT LIST)	500	500	2000
Viewable Audit Trail ON KEYPAD OLED(50 EVENTS)	NO	NO	YES	YES	YES
Downloadable Audit Trail	NO	NO	YES	YES	YES
Audit time and date stamp	NO	NO	YES	YES	YES
Dual Mode	NO	YES	YES	YES	YES
Silent Alarm	NO	YES	YES	YES	YES
Duress	NO	YES	YES	YES	YES
Remote Lock out	NO	YES	YES	YES	YES
Wrong Try Penalty	YES	YES	YES	YES	YES
Dual Credential	NO	NO	NO	YES	YES
Bluetooth Dual Credential	NO	NO	NO	YES	YES
Number of Locks	1	1	1	2	5
Bolt Switch	NO	NO	YES	YES	YES
Reset Function	YES	YES	YES	YES	YES
Power	2 x 9 volts	2 x 9 volts	2 x 9 volts	2 x 9 volts	2 x 9 volts
AC Power option	YES	YES	YES	YES	YES
Master Reset by code or Zapbox	YES	YES	YES	YES	YES
Keypad Functional Configuration	YES	YES	YES	YES	YES
Software Functional Configuration	NO	YES	YES	YES	YES